

Please amend the claims as follows:

1 1. (further amended) A translation loop modulator for a transmission circuit in a
2 communication system having a first mode of operation at a first frequency and a second mode
3 of operation at a second frequency, said translation loop modulator comprising:
4 input modulation means for receiving at least one input signal that is representative of
5 information to be modulated, for receiving a feedback signal, and for producing an intermediate
6 modulated signal responsive to said input signal and said feedback signal;
7 comparator means for receiving said intermediate modulated signal and a reference signal
8 having a frequency of F_{LO} , and for producing an output transmission signal having a frequency
9 F_{OUT} responsive to said intermediate modulated signal, wherein said comparator means includes
10 a first frequency divider unit for providing a divide by m function and a second frequency divider
11 unit for providing a divide by n function such that $F_{LO} = F_{OUT} / (1 + m/n)$ in said first mode of
12 operation and $F_{LO} = F_{OUT} / (1 - m/n)$ in said second mode of ~~operation~~ **operation**; and
13 feedback circuitry coupled to said output transmission signal, coupled to said reference
14 signal and coupled to said input modulation means, said feedback circuitry for producing said
15 feedback signal responsive to said output transmission signal and said reference signal.

1 2. (original) A translation loop modulator as claimed in claim 1 further comprising a
2 reference loop modulator for producing said reference signal.

1 3. (original) A translation loop modulator as claimed in claim 2, wherein said reference loop
2 modulator includes a fractional n synthesizer.

1 4. (previously canceled).

1 5. (previously amended) A translation loop modulator as claimed in claim 1, wherein an
2 input port of said second frequency divider unit is coupled to said reference signal, and an output
3 port of said second frequency divider unit is coupled to a phase comparator device.

1 6. (previously canceled).

1 7. (previously amended) A translation loop modulator as claimed in claim 1, wherein an
2 input port of said first frequency divider unit is coupled to said intermediate modulated signal,
3 and an output port of said first frequency divider unit is coupled to a phase comparator device.

El
cont
1 8. (original) A translation loop modulator as claimed in claim 1, wherein said feedback
2 circuitry includes a mixer device including a first input port coupled to said output transmission
3 signal, a second input port coupled to said reference signal, and an output port coupled to said
4 feedback signal.

1 9. (original) A translation loop modulator as claimed in claim 8, wherein said reference
2 signal is directly connected to said mixer device.

1 10. (previously amended) A translation loop modulator for a transmission circuit in a
2 communication system having a first mode of operation at a first frequency and a second mode
3 of operation at a second frequency, said translation loop modulator comprising:
4 quadrature modulation means for receiving at least one input signal that is representative

5 of information to be modulated, for receiving a feedback signal, and for producing an quadrature
6 modulated signal responsive to said input signal and said feedback signal;

7 phase comparator means for receiving said quadrature modulated signal and a reference
8 signal having a frequency F_{LO} , and for producing a phase comparator signal responsive to said
9 quadrature modulated signal and said reference signal, said phase comparator means including a
10 first frequency divider unit for providing a divide by m function and a second frequency divider
11 unit for providing a divide by n function;

12 oscillator means for receiving said phase comparator signal, and for producing an output
13 transmission signal responsive to said phase comparator signal, said output transmission signal
14 having a frequency F_{OUT} wherein $F_{LO} = F_{OUT} / (1 + m/n)$ in said first mode of operation and F_{LO}
15 $= F_{OUT} / (1 - m/n)$ in said second mode of operation; and

16 feedback circuitry coupled to said output transmission signal, coupled to said reference
17 signal and coupled to said quadrature modulation means, said feedback circuitry for producing
18 said feedback signal responsive to said output transmission signal and said reference signal.

1 11. (original) A translation loop modulator as claimed in claim 10 further comprising a
2 reference loop modulator for producing said reference signal.

1 12. (original) A translation loop modulator as claimed in claim 11, wherein said reference
2 loop modulator includes a fractional n synthesizer.

1 13. (previously canceled).

1 14. (previously amended) A translation loop modulator as claimed in claim 10, wherein an

2 input port of said second frequency divider unit is coupled to said reference signal, and an output
3 port of said second frequency divider unit is coupled to a phase comparator device.

1 15. (previously canceled).

1 16. (previously amended) A translation loop modulator as claimed in claim 10, wherein an
2 input port of said first frequency divider unit is coupled to said intermediate modulated signal,
3 and an output port of said first frequency divider unit is coupled to a phase comparator device.

1 17. (original) A translation loop modulator as claimed in claim 10, wherein said feedback
2 circuitry includes a mixer device including a first input port coupled to said output transmission
3 signal, a second input port coupled to said reference signal, and an output port coupled to said
4 feedback signal.

1 18. (previously amended) A translation loop modulator as claimed in claim 17, wherein said
2 reference signal is directly connected to said mixer device.

1 19. (previously amended) A translation loop modulator for a transmission circuit in a
2 communication system having a first mode of operation at a first frequency and a second mode
3 of operation at a second frequency, said translation loop modulator comprising:
4 quadrature modulation means for receiving at least one input signal that is representative
5 of information to be modulated, for receiving a feedback signal, and for producing an quadrature
6 modulated signal responsive to said input signal and said feedback signal;
7 first frequency divider means for receiving said quadrature modulated signal, and for

8 producing a first frequency divided signal responsive to said quadrature modulated signal such
9 that said first frequency divider means provides a divide by m function;
10 second frequency divider means for receiving a reference signal having a frequency F_{LO} ,
11 and for producing a second frequency divided signal responsive to said reference signal such that
12 said second frequency divider means provides a divide by n function;
13 phase comparator means for receiving said first frequency divided signal and said second
14 frequency divided signal, and for producing a phase comparator signal responsive to said first
15 and second frequency divided signals;
16 oscillator means for receiving said phase comparator signal, and for producing an output
17 transmission signal having a frequency F_{OUT} responsive to said phase comparator signal such
18 that $F_{LO} = F_{OUT} / (1 + m/n)$ in said first mode of operation and $F_{LO} = F_{OUT} / (1 - m/n)$ in said
19 second mode of operation; and
20 feedback circuitry coupled to said output transmission signal, coupled to said reference
21 signal and coupled to said quadrature modulation means, said feedback circuitry for producing
22 said feedback signal responsive to said output transmission signal and said reference signal.

1 20. (original) A translation loop modulator as claimed in claim 19 further comprising a
2 reference loop modulator for producing said reference signal.

1 21. (previously added) A translation loop modulator as claimed in claim 19, wherein said
2 first mode of operation is at about 1800 MHz.

1 22. (previously added) A translation loop modulator as claimed in claim 19, wherein said

El
concl 2 second mode of operation is at about 900 MHz.
